

## Features:

- Analog Multimeter with Mirror Scale
- Inbuilt Buzzer and LED
- $0\Omega$  Adjustable with x 100 Range
- Transistor Test, hFE with Diode

### DC VOLTAGE

Range	Resolution	Accuracy
0.1mV~1000V	20K $\Omega$ /V	3; for 1000V ; 5

### DC CURRENT

Range	Resolution	Accuracy
50 $\mu$ A~10A	-	3; for 10V ; 5

### AC VOLTAGE

Range	Resolution	Accuracy
10V~1000V	9K $\Omega$ /V	4; for 1000V ; 5

### POWER

AA 1.5V x 2

9V (6F22) x 1

## Special Function

Diode Test	✓	Function Protection	✓
Transistor Testing	✓	Continuity Buzzer	About 100 $\Omega$

- Standard Accessories : Test Lead, Manual
- Dimension : 148(H) x 100(W) x 35(D)mm

### RESISTANCE

Range	Resolution	Accuracy
0.2 $\Omega$ ~2k $\Omega$	-	3
2 $\Omega$ ~20k $\Omega$		
20 $\Omega$ ~200k $\Omega$		
200 $\Omega$ ~2M $\Omega$		
2k $\Omega$ ~20M $\Omega$		

## YX-360 TRE-B

