

Sound Level Meter

SL-1352



Features:

- Max & Min Measurement
- Over Range Display / Under range display
- A & C Weighting
- FAST & SLOW response
- Adjustable Alarm Levels
- Backlight / DATA LOGGING
- **USB Computer Interface** (advanced Software program for all Windows)

Technical Data:

Basic Function	Range
Accuracy	1.4dB
Resolution	0.1dB
Frequency Range	31.5Hz ~8kHz
Dynamic Range	50dB
Level Range	Low: 30dB~80dB Medium: 50dB~100dB High: 80dB~130dB Auto: 30dB~130dB
Time Wiegthing	FAST (125mS), SLOW (1s)
Microphone	½ inch electric condenser microphone
Display Update	2 times/sec
Analog Output	AC/DC outputs, AC=1Vrms, DC=10mV/dB



- **Standard Accessories** : Gift Box with Hard Carrying Case, Manual , Battery, Screwdriver, Audio Plug, Windscreen, & DC 9V power supply, HTC USB with Software
- **Dimension** : 252(H) x 66(W) x 33(D)mm